

# RGB LED, 5 mm



## Features

- Uniform light output
- Low power consumption
- I.C. compatible
- Long life solid state reliability
- Compliance with EU REACH
- The product itself will remain within RoHS compliant Version



## Applications

- TV set
- Monitor
- Telephone
- Computer
- Circuit board, etc

## Descriptions

- The Super Bright Red source color devices are made with AlGaNp on GaAs substrate Light Emitting Diode
- The Pure Green source color devices are made with InGaN on Sapphire substrate Light Emitting Diode
- The Blue source color devices are made with InGaN on Sapphire substrate Light Emitting Diode

## Abosolute Maximum Ratings at Ta 25°C

Parameters	Symbol	Max.	Unit
Power Dissipation	Red	60	mW
	Pure Green	90	
	Blue	90	
Peak Forward Current <sup>(a)</sup>	IPF	100	mA
DC Forward Current <sup>(b)</sup>	Red	25	mA
	Pure Green	25	
	Blue	25	
Reverse Voltage	VR	5	V
Operating Temperature Range	Topr	-40°C to +85°C	
Storage Temperature Range	Tstg	-40°C to +100°C	
Soldering Temperature	Tsld	260°C for 5 Seconds	

### Notes:

- a. Derate linearly as shown in derating curve.
- b. Duty Factor = 10%, Frequency = 1 kHz.

## Device Selection Guide

Part No.	Emitting Color	Lens Color
	Super Bright Red	
RND 135-00192	Pure Green	Water Clear
	Blue	

# RGB LED, 5 mm



## Electrical Optical Characteristics at Ta 25°C

Parameters	Symbol	Emitting Color	Min.	Typ.	Max.	Unit	Test Condition
Luminous Intensity <sup>(a)</sup>	I <sub>v</sub>	Red	600	1000	---		
		Pure Green	2000	4000	---	mcd	IF=20mA
		Blue	400	700	---		
Viewing Angle <sup>(b)</sup>	2θ <sub>1/2</sub>	Red	---	25	---		
		Pure Green	---	25	---	deg.	IF=20mA
		Blue	---	25	---		
Peak Emission Wavelength	λ <sub>p</sub>	Red	---	632	---		
		Pure Green	---	520	---	nm	IF=20mA
		Blue	---	468	---		
Dominant Wavelength <sup>(c)</sup>	λ <sub>d</sub>	Red	---	624	---		
		Pure Green	---	525	---	nm	IF=20mA
		Blue	---	470	---		
Spectral Line Half-Width	△λ	Red	---	20	---		
		Pure Green	---	20	---	nm	IF=20mA
		Blue	---	25	---		
Forward Voltage	VF	Red	1.6	2.0	2.4		
		Pure Green	2.6	3.2	3.6	V	IF=20mA
		Blue	2.6	3.2	3.6		
Reverse Current	IR	Red	---	---	10		
		Pure Green	---	---	10	μA	VR=5V
		Blue	---	---	10		


### Notes:

- Luminous intensity is measured with a light sensor and filter combination that approximates the CIE eye-response curve.
- 2θ<sub>1/2</sub> is the o-axis angle where the luminous intensity is 1/2 the peak intensity.
- The dominant wavelength (λ<sub>d</sub>) is derived from the CIE chromaticity diagram and represents the single wavelength which defines the color of the device.

# RGB LED, 5 mm



## Package Dimensions









### Notes:

1. All dimensions are in millimeters (inches).
2. Tolerance is  $\pm 0.25$  mm (.010") unless otherwise noted.
3. Protruded resin under flange is 1.00mm (.039") max.

# RGB LED, 5 mm

## Typical Electrical / Optical Characteristics Curves (25°C Ambient Temperature Unless Otherwise Noted)







Red:



# RGB LED, 5 mm









Green:



# RGB LED, 5 mm



Blue:



# RGB LED, 5 mm



## Cautions

### 1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

### 2. Storage

2.1 The LEDs should be stored at 30°C or less and 70%RH or less after being shipped from RND and the storage life limits are 3 months. If the LEDs are stored for 3 months or more, they can be stored for a year in a sealed container with a nitrogen atmosphere and moisture absorbent material.

2.2 Please avoid rapid transitions in ambient temperature, especially, in high humidity environments where condensation can occur.

### 3. Cleaning

Use alcohol-based cleaning solvents such as isopropyl alcohol to clean the LEDs if necessary.

### 4. Lead Forming & Assembly

During lead forming, the leads should be bent at a point at least 1.6mm from the base of LED lens. Do not use the base of the lead frame as a fulcrum during forming. Lead forming must be done before soldering, at normal temperature. During assembly on PCB, use minimum clinch force possible to avoid excessive mechanical stress.

### 5. Soldering

When soldering, for Lamp without stopper type and must be leave a minimum of 3mm clearance from the base of the lens to the soldering point. Do not apply any external stress to the lead frame during soldering while the LED is at high temperature.



Recommended soldering conditions:

Soldering Iron		Wave Soldering	
Temperature	300°C Max.	Pre-heat Pre-heat Time	100°C Max.
Soldering Time	3 sec. Max. (one time only)	Solder Wave Soldering Time	60 sec. Max. 260°C Max. 5 sec. Max.

Note: Excessive soldering temperature and / or time might result in deformation of the LED lens or catastrophic failure of the LED.

### 6. Drive Method

An LED is a current-operated device. In order to ensure intensity uniformity on multiple LEDs connected in parallel in an application, it is recommended that a current limiting resistor be incorporated in the drive circuit, in series with each LED as shown in Circuit A below.



- (A) Recommended circuit
- (B) The brightness of each LED might appear different due to the differences in the I-V characteristics of those LEDs.

## 7. Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used. It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.

## 8. ESD (Electrostatic Discharge)

Static Electricity or power surge will damage the LED. Suggestions to prevent ESD damage:

8.1. Use a conductive wrist band or anti- electrostatic glove when handling these LEDs.

8.2. All devices, equipment, and machinery must be properly grounded.

8.3. Work tables, storage racks, etc. should be properly grounded.

8.4. Use ion blower to neutralize the static charge which might have built up on surface of the LEDs plastic lens as a result of friction between LEDs during storage and handing.

ESD-damaged LEDs will exhibit abnormal characteristics such as high reverse leakage current, low forward voltage, or "no light up" at low currents.

To verify for ESD damage, check for "light up" and VF of the suspect LEDs at low currents.

The VF of "good" LEDs should be >2.0V@0.1mA for InGaN product and >1.4V@0.1mA for AlInGaN product.

## 9. Others

9.1 The information included in this document reflects representative usage scenarios and is intended for technical reference only.

9.2 The part number, type, and specifications mentioned in this document are subject to future change and improvement without notice. Before production usage customer should refer to the latest datasheet for the updated specifications.

9.3 When using the products referenced in this document, please make sure the product is being operated within the environmental and electrical limits specified in the datasheet. If customer usage exceeds the specified limits, RND will not be responsible for any subsequent issues.

9.4 The LEDs described here are intended to be used for ordinary electronic equipment (such as office equipment, communication equipment and household applications). Consult RND Sales in advance for information on applications in which exceptional reliability is required, particularly when the failure or malfunction of the LEDs may directly jeopardize life or health, such as in aviation, transportation, traffic control equipment, medical and life support systems and safety devices.